



# LTE-M compatible STREET LIGHTING REMOTE MANAGEMENT & SMART CITY PLATFORM



[FRCMv4-M1 - LTE-M compatible lighting panel control and monitoring unit - data sheet] December 4, 2018 Ver 1.0

## FRCMv4-M1 – LTE-M compatible LIGHTING PANEL CONTROL & MONITORING UNIT

Installed inside the feeder pillar, it is designed to provide autonomous operation for street lighting installations and to carry out three phase measurements and analysis of electrical parameters in street lighting grids.

- › **VPN security** with AES128/256-bit encryption and key rotation.
- › **Bandwidth efficient** with minimal communication requirements.
- › **Autonomous operation** based on predefined astronomic calendar and/or external light level sensor (digital INPUT).
- › **Remote real-time ON/OFF control.**
- › **Remote monitoring** of grid parameters in street lighting grids: per phase voltage, current, frequency, power factor, active/ reactive/ apparent power, daily active/ reactive energy consumption.
- › **Configuration options** for: current transformer ratio, voltage/power thresholds and daytime/nighttime consumption thresholds.
- › **LCD** for displaying electrical parameters and device status.
- › **GPS** for exact location and time.
- › **Maintenance switch** for local manual override (AUTO/ON/OFF).
- › **Inputs:** 2 x Digital input.
- › **Output:** 1 x Dry contact relay output (230V, max 12A).
- › Designed **lifetime: 10+** years.

LTE-M Compatible



**FLASHNET**


4A Fundatura Harmanului Street / Brasov 500240, ROMANIA  
Phone: +40 268 333 766 / info@flashnet.ro / www.intelilight.eu



# LTE-M compatible STREET LIGHTING REMOTE MANAGEMENT & SMART CITY PLATFORM



[FRCMv4-M1 - LTE-M compatible lighting panel control and monitoring unit - data sheet] December 4, 2018 Ver 1.0



**PLUG & PLAY  
ADAPTABLE  
to EXISTING  
STREET LIGHTING  
INFRASTRUCTURE**

**SCALABLE &  
IMMEDIATELY  
OPERABLE**



**up to  
35%  
ENERGY  
SAVINGS**



**up to  
42%  
MAINTENANCE  
COST REDUCTION**

## FRCMv4-M1 lighting panel control and monitoring unit

Product description	Street lighting panel control and monitoring unit
Power supply	Direct connection
Power consumption	Max. 10 W
Network interface	NB-IoT / LTE-M / GSM
LTE supported frequencies	worldwide
Security	AES128/256-bit encryption and key rotation per session
Voltage input range	0V - 265V / 45-65 Hz
Input	<ul style="list-style-type: none"> <li>• R, S, T voltage inputs</li> <li>• R, S, T, N current inputs</li> <li>• 2 x Digital input</li> </ul>
Power network type	Three phase electric network and Neutral
Current transformers	Standard X:5, where X is user definable
Operating temperature	-25°C to + 80°C
Operating humidity	95% non-condensing
Connectors	Voltage (R,S,T,N), Current (R,S,T,N), RF / GPS / USB
Grid connectors	2.5 mm <sup>2</sup> terminals
Antennas	2 x SMA
Output	1 x Dry contact relay (230V, max 12A)
Display	LCD
Precision Real Time Clock (RTC)	Battery operated
Battery operation time	Up to 12 hours
GPS	Location and time
Dimensions (L x W x H)	138 x 90 x 47 mm
IP rating	IP42 (optional IP67 external housing)
Certifications	CE FCC ( in progress)

### MEASUREMENTS:

- › voltage
- › current
- › active power
- › reactive power
- › apparent power
- › active energy
- › reactive energy
- › power factor
- › frequency

### CONFIGURABLE PARAMETERS:

- › current transformer ratio
- › voltage/power/ current thresholds
- › daytime/ nighttime consumption threshold

### GENERATED ALARMS:

- › over/ under voltage detection
- › over/ under power detection
- › over/ under current detection
- › unusual daytime/nighttime consumption
- › phase failure



**FLASHNET**

4A Fundatura Harmanului Street / Brasov 500240, ROMANIA  
Phone: +40 268 333 766 / info@flashnet.ro / www.intelilight.eu